

MOTOR AKIMLARI VE KABLO KESİTLERİ

MOTOR GÜCÜ		COSφ	VERİM2(%)	ÇEKTİĞİ AKIM(A)	KUL.SİGORTA		KONTAKTÖR (A)			TERMİK RÖLE(A)			TEL KESİTİ(mm²)				
KW	HP				DİREKT	* - Δ	DİREKT	* - Δ			DİREKT	* - Δ	DİREKT	* - Δ			
								N	Δ	*							
0,8	0,25	0,34	1	62	0,8	2	-	9	-	-	-	0,6-1	-	2,5	-		
1,1	0,37	0,5	1	64	1,1	4	-	9	-	-	-	1,1-1,6	-	2,5	-		
1,5	0,55	0,75	1	59	1,5	4	-	9	-	-	-	1,1-1,6	-	2,5	-		
1,9	0,75	1	1	74	1,9	6	-	9	-	-	-	1,7-2,5	-	2,5	-		
2,7	1,1	1,5	1	77	2,7	6	-	9	-	-	-	2,2-3,2	-	2,5	-		
3,6	1,5	2	1	78	3,6	10	-	9	-	-	-	3-4,5	-	2,5	-		
5,2	2,2	3	1	81	5,2	10	-	9	-	-	-	4-5	-	2,5	-		
6,8	3	4	1	81	6,8	16	-	16	-	-	-	5-7,5	-	2,5	-		
9	4	5,5	1	82	9	20	-	16	-	-	-	6,5-9,5	-	2,5	-		
11,5	5,5	7,5	1	83	11,5	25	20	16	16	16	16	8-12	5-7,5	4	2x2,5		
15,5	7,5	10	1	85	15,5	35	25	32	16	16	16	11-16	6-12	4	2x2,5		
21	11	15	1	87	21	35	35	32	32	32	16	17-25	11-16	4	2x2,5		
29	15	20	1	87	29	50	35	45	32	32	16	22-32	17-25	6	2x4		
36	18,5	25	1	88	36	63	50	45	32	32	16	30-45	17-25	10	2x4		
41	22	30	1	89	41	63	63	63	32	32	16	40-63	22-32	10	2x6		
55	30	40	1	90	55	80	63	63	45	45	32	40-63	30-45	16	2x6		
67	37	50	1	90	67	100	80	110	63	63	45	55-80	30-45	25	2x10		
80	45	60	1	91	80	125	100	110	63	63	45	70-100	40-63	35	2x16		
99	55	75	1	91	99	160	125	170	110	110	63	90-110	55-80	50	2x16		
132	75	100	1	91	132	200	160	170	170	170	110	120-170	70-100	70	2x25		
157	90	120	1	92	157	225	200	250	170	170	110	120-170	90-110	70	2x35		
KONTAKTÖR ANMA AKIM(A)					9	9	16	16	16	32	32	45	63	110	110	170	240
KONTAKTÖR SERİSİ(Boy)					0	0	1	1	1	2	2	3	4	6	6	8	9
KAPAYAN KONTAK(S)					1	-	2	1	2	2	2	4	4	4	3	4	-
AÇAN KONTAK(Ö)					-	1	-	1	2	2	2	2	2	2	3	2	-
BOBİN GÜCÜ WAT	KAPAMA ESNASI		50	50	65	65	65	100	100	250	300	650	650	900	-		
	KAPANDIKTAN SONRA		8	8	8	8	8	10	10	20	30	50	50	65	-		

AC3=P/560

AC1=P/657

30/5 boy 6,5 kg.

40/5 boy 8 kg.

ÜR-2 - 0,37kW. - 1,1 (1-1,6)
 n-4 - 0,75kW. - 1,9 (1,6-2,5)
 n-6 - 1,5 kW. - 3,6 (2,5-4)